5.17_V2.0 SWITCH FROM BEP B TO BEP A

Last Revised: May 26, 2016
Filename: switch_bepb_a

BRIEF FUNCTIONAL DESCRIPTION:

This is a contingency procedure to switch from using BEP B to using BEP A.

The sequence of actions will be:

1. Issue power-down command for FEPs and video boards
2. Select BEP A
3. Cold boot BEPs
4. Verify BEP A boots from SW TLM
5. Check HW LEDs
6. Check SW LEDs
7. Issue power-down command for FEPs and video boards

The procedure does a cold boot to get the instrument into a known state, so if there were patches loaded into BEP A they will be lost. The operator should be cognizant if patches must be subsequently loaded. The final power-down command ensures that the control register in the newly active BEP reflects the current FEP power status.

ASSUMED INSTRUMENT STATE:

Assumes that DPA A & B are on.
Assumes BEP B is functional and can accept a power-down command.

SPECIAL INITIAL CONDITIONS:

None.

OPERATIONAL CONSTRAINTS/CAUTIONS:

Any patches loaded into BEP A will be removed as a result of this procedure. This procedure resets the focal plane temperature setting.

REFERENCES:

CHANGE HISTORY:

V1.0

- Initial version, based on switch_bepa_b V2.1
- Added warnings about focal plane temperature setting.
- Minor formatting change to table.
- Added steps to power down FEPs and video boards before and after the switch.
- Added intiial state for BEP B.

V2.0

- ACIS team signed-off version.

This page is intentionally blank

Table 1: **SWITCH FROM BEP B TO BEP A(Page 1)**

Step #	Title (Revision 5.17_V2.0)	Time Req (m)	Command Description	Command Mnemonic	Telemetry Description	Telemetry Mnemonic	Expected Value
1	**Issue Power Command**						
1.1	Power off FEPs & Video Boards	1	changeConfigSetting	WSPOW00000			
2	**Select BEP A**						
2.1	Select BEP A	1		1BSELICL(0)			
3	**Cold Boot BEPs**						
3.1	Set boot modifier off	1	DPA Boot Modifier	1BMODIBM(0)			
3.2	Set warm boot flag off	1	DPA Cold Boot	1WRMBTSB(0)			
3.3	Halt BEP	1	DPA Command Reset	1RSETIRT(1)			
3.4	Restart BEP	1		1RSETIRT(0)			
3.5	Check BEP A Boot	2					
3.6	Check HW LEDs	2			BEP Select BEP FIFO Not Full BEP FIFO Not Empty	1STAT4ST 1STAT6ST 1STAT7ST	0 1 0
3.7	Check SW LEDs	2			BEP initialization Watchdog boot Science run status	1STAT3ST 1STAT2ST 1STAT1ST 1STAT0ST	0 1 1 0or1

Table 1: **SWITCH FROM BEP B TO BEP A(Page 1)**

Step #	Units	Telemetry EGSE	Other Verifier	Crit	Description	Notes	RT Con	Tlm Fmt	Min Alt	SIM Pos
1										
1.1		Verify cmdResult==1 commandEcho 773		1 1			Y	1or2		
2										
2.1					1BSELICL=0 selects BEP A		Y	1or2		
3										
3.1					Disable uplink boot		Y	1or2		
3.2					Cold boot active BEP		Y	1or2		
3.3					Hold active BEP reset line		Y	1or2		
3.4					Release BEP reset line		Y	1or2		

3.5		Check bepStartupMessage:
		bepTickCounter < 10; version=11;
		warmBootFlag = 0;
		patchValidFlag = 1
		Check swHousekeeping messages:
		startingBepTickCounter < 10;
		endingBepTickCounter=
		startingBepTickCounter+640;
		version = 11
				1
				1
				1
				1
				
				2
				2
				
				1
							Y	1or2		

3.6				2 2 2	0 indicates BEP A is selected 1 means FIFO not full 0 means FIFO empty		Y	1or2		
3.7				1 2 2 2	0 means BEP SW is running 1 means no watchdog boot 1 means science idle This bit toggles to indicate BEP is running		Y	1or2		

Table 1: **SWITCH FROM BEP B TO BEP A(Page 2)**

Step #	Title (Revision 5.17_V2.0)	Time Req (m)	Command Description	Command Mnemonic	Telemetry Description	Telemetry Mnemonic	Expected Value
4	**Issue Power Command**						
4.1	Power off FEPs & Video Boards	1	changeConfigSetting	WSPOW00000			
	Total Time:	13					

Table 1: **SWITCH FROM BEP B TO BEP A(Page 2)**

Step #	Units	Telemetry EGSE	Other Verifier	Crit	Description	Notes	RT Con	Tlm Fmt	Min Alt	SIM Pos
4										
4.1		Verify cmdResult==1 commandEcho 773		1 1			Y	1or2		